

LG5100i-R Digital Inverter Gasoline Generator (NEW) LG5100i-R (3.5KW)



✓ Mechanical Speed Governor System (1.5KW, 2.5KW, 3.5KW)



Load Governing Lever

Output indicator

3 LEVEL ADJUSTABLE OUTPUT INDICATOR		
	1.5KW (2800RPM)	
	2.5KW (3200RPM)	
	3.5KW (3600RPM)	



✓ Stable power output

Inverter system ensures stable high-quality output for computers and other sensitive equipment (**Waveform distortion rate: 3%**).

√ **HIGH FUEL EFFICIENCY! SAVE FUEL!**

√ **Start at 100% power equipment loading!**

Specification:

GENSET Model	LG5100i-R
Rated frequency (Hz)	50
Rated voltage (V)	230
Rated current (A)	15.2
Rated output power (kW)	1.5 / 2.5 / 3.5 (3-level adjustable output)
Max output power (kW)	3.8
DC output	None
Alternator type	Rare earth permanent-magnet, 100% copper winding
Voltage regulator	Inverter
Engine model	LG168F-2
Engine type	4-stroke, single-cylinder, OHV gasoline engine
Bore × Stroke (mm)	68×54
Displacement (cc)	196
Compression ratio	8.5:1
Rated power (kW/rpm)	4.8 (6.5HP) / 3600
Rated engine speed (rpm)	2800 / 3200 / 3600
Fuel capacity (L)	9
Fuel consumption (L / H)	1.36
Cont. running time (Hrs.)	7
Starting system	Recoil & Electric starter with battery
Noise level dB/7M	68
Packing size (L×W×H) (MM)	505×405×460
Net / Gross weight (KG)	35 / 37

Prodaja in servis: Garancija 1 leto

AGREGAT SERVICE d.o.o., Dolsko 29, 1262 Dol pri Ljubljani Mail: agregat.service@siol.net

GSM: +386 41 665 518